

POWER TWISTER 1/4" SHANK

For closing twist wire boxes and crates



DIRECTIONS FOR USE

1. After the crate is prepared for closing, the wires are bent at right angles to the crate approximately 5/8" from the closing edge.
2. The end of the bit is pushed over the wires and against the box or crate. The trigger is pulled and held for about two seconds to form a twist. The tool is then removed from the finished twist.
3. After all of the twists are completed, they are knocked against the box or crate - parallel to the binding wire.

Power Twisters and separate bits may be obtained from manufacturers of wirebound boxes and from Stapling Machines Co., Rockaway, N.J. When ordering a complete tool or bit only, specify the Catalog Number (or Bulletin No. T-18) for the gage of wire to be twisted.

Wire	Catalog Number	
	Complete Tool	Bit Only
12 or 13 gage	1A 148.680	137.89
13 or 14 gage	2A 148.680	137.88
14 or 15 gage	3A 148.680	137.85
15 or 16 gage	4A 148.680	137.78

The Power Twister is a fast, light-weight tool used for closing twist wire (Style 1) wirebound boxes and crates. It is recommended where the closing of twist wire boxes is a full time operation. The Power Twister consists of a motor (1/4" heavy-duty), that fits all of the four sizes of bits.

